

SFP28
25GBASE-SR

Quick Start

P/N: 1700487F1

DESCRIPTION

The 25GBASE-SR SFP28 is a short range SFP28 optical device designed for 25 G Ethernet applications.

This SFP28 supports the following features:

- Up to 28 Gbps Data Links
- Maximum link length of 70 m on OM3 or 100 m on OM4 multi-mode fiber
- Power dissipation < 1 W
- VSCSEL laser and PIN receiver
- Metal enclosure for lower EMI
- Two-wire interface with integrated Digital Diagnostic monitoring
- Hot pluggable SFP+ footprint
- Compliant with SFF-8472
- Compliant with SFP+ MSA with LC connector
- Single 3.3 V power supply

Applications:

- 25 G Ethernet
- Data center and Fiber channel

**CAUTION!**

Due to compliance certification requirements, use only pluggable optics supplied by Adtran. Adtran cannot certify system integrity with other pluggable optics.

INSTALLATION

Before installing the equipment, inspect the SFP28. If damage has occurred during shipping, file a claim with the carrier, and then contact Adtran Customer Support. For more information, refer to the warranty.

**NOTE**

A 1 m direct interconnect cable designed for use with SFP28 optical devices is available from Adtran (P/N 1700489F1).

Installation Steps

To install the SFP28 into an appropriate device, complete the following steps:

**NOTE**

- Do not remove the protective dust cover from the SFP28 until the fiber optic cable is ready to be connected.
- Orientation of the SFP28 will vary depending on the module.

1. Insert the SFP28 into the SFP+ cage on the module.
2. Slide the SFP28 all the way into the SFP+ cage until there is an audible “click”.
3. Continue the installation and turn-up of the host module using the instructions in the Job Aid or Quick Start provided with the module or other system-level documentation available online at www.adtran.com.

**NOTE**

The latch on the SFP28 is for removal only. When removing the SFP28, rotate the latch away from the SFP28. It should easily slide out of the cage.

**WARNING!**

WARNING indicates a hazard which, if not avoided, could result in death, injury or serious property damage.

**CAUTION!**

CAUTION indicates a hazard which, if not avoided, could result in service interruption, damage to the equipment, or minor property damage.

**NOTE**

NOTES inform the user of additional, but important, information or features.

SPECIFICATIONS

General

- Module Type: SFP28
- Media Type: Fiber
 - ◆ Multi-Mode/Dual
- LC Connector
- Signal Data Rate: 25.78 Gbps
- Distance:
 - ◆ OM4: 100 m
 - ◆ OM3: 70 m

Optical

- Transmitter
 - ◆ Laser Diode Type: VSCSEL
 - ◆ Transmit Wavelength: 850 nm
 - ◆ Tx Power: -8.4 dBm to +2.4 dBm
 - ◆ Spectral Width: 0.6 nm
 - ◆ Extinction Ratio: 2.0 dB
- Receiver
 - ◆ Type: PIN
 - ◆ Central Wavelength: 850 nm
 - ◆ Receiver Sensitivity: -10.3 dBm
 - ◆ Receiver Overload: 2.4 dBm

Environmental

- Protected Equipment Severe Environment (Outdoor)
 - ◆ System Ambient Operational Temperature Range: -40°C to +65°C
 - ◆ Storage Temperature Range: -40°C to +85°C
 - ◆ Relative Humidity: 5% to 95%, non-condensing

SAFETY AND REGULATORY

ENGLISH



WARNING!

Read all warnings, cautions, notes, and installation instructions before installing or servicing this equipment.



CAUTION!

This product is a Class 1 Laser module that complies with FDA 21 CFR 1040.10, 1040.11 and IEC 60825-1.



CAUTION!

- Electrostatic Discharge (ESD) can damage electronic devices. When handling devices, wear an antistatic discharge wrist strap to prevent damage to electronic components. Place devices in antistatic packing material when transporting or storing. When working on devices, always place them on an approved antistatic mat that is electrically grounded.
- This product and the host system are designed and intended for installation as part of either a Common Bonding Network (CBN) or Isolated Bonding Network (IBN).
- This product's outer case is "electrically isolated" from other circuits, as a result, this product can be used in systems that are installed either in a DC-I (isolated) or DC-C (common) configuration. For Systems where other installed modules or the host system itself have internal connections between battery return and frame ground, the system can only be deployed in a DC-C configuration.
- If the host system has a protective earth (PE) terminal, the PE terminal of the host system must be connected to protective earth (PE) to ensure that the exposed metal (i.e., front panels, optical modules) on the product is properly grounded.

**NOTE**

- This product is designed to be deployed in GR-3108-CORE environmental Class 1, 2, or 3.
- This product is NRTL Listed to the applicable UL Standards. The product is designed to meet the applicable requirements of Telcordia GR-63-CORE, GR-1089-CORE and GR-3108-CORE. This product has also been evaluated to applicable international standards and meets the requirements for CE marking.
- This product is intended for deployment in locations such as Central Offices and outside plant cabinets. This product is to be installed and serviced by trained and qualified Service personnel only.
- This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions:
 1. This device may not cause harmful interference.
 2. This device must accept any interference received, including interference that may cause undesired operation.
- Changes or modifications not expressly approved by Adtran will void the warranty.
- This product is designed to meet the following environmental classes:
 - ◆ ETSI EN 300 019-1-1 "Classification of environmental conditions; Storage," Class 1.2
 - ◆ ETSI EN 300 019-1-2 "Classification of environmental conditions, Transportation," Class 2.3
 - ◆ ETSI EN 300 019-1-3 "Classification of environmental conditions, Stationary use at weather protected locations," Class 3.3. This product is designed to function without degradation during exposure to all test severities per Class 3.3.
- This product meets EU RoHS Directive. Refer to www.adtran.com for further information on RoHS/WEEE.

FRANÇAIS**AVERTISSEMENT!**

Lisez toutes les mentions de danger et de prudence et les remarques, ainsi que la notice d'installation, avant d'effectuer l'installation ou l'entretien de cet équipement.

**ATTENTION!**

Ce produit est un laser de classe 1 conforme à la norme FDA 21 CFR 1040.10 et 1040.11 et IEC 60825-1.

**ATTENTION!**

- L'ESD (décharge électrostatique) peut endommager les modules électroniques. Lors de la manipulation des modules, portez un bracelet de décharge antistatique pour éviter d'endommager les composants électroniques. Placez les modules dans un emballage antistatique lors du transport ou du stockage. Lorsque vous travaillez sur les modules, placez-les toujours sur un tapis antistatique certifié muni d'un branchement de mise à la terre.
- Ce produit et système hôte sont conçus et destinés à être installés dans le cadre soit d'un réseau commun Bonding (CBN) ou isolé Réseau Bonding (IBN).
- Si le système hôte est doté d'une borne de mise à la terre de protection (PE), la borne PE du système hôte doit être connectée à la mise à terre de protection (PE), afin d'assurer que les parties métalliques à découvert (panneaux frontaux, modules optiques) du produit soient correctement mis à terre.

**REMARQUE**

Ce produit est conforme à la directive européenne RoHS. Reportez-vous à www.adtran.com pour de plus amples renseignements sur RoHS.

DEUTSCH

WARNUNG!

Lesen Sie alle Warnungen, Gefahrenhinweise, Anmerkungen und Installationsanweisungen bevor Sie dieses Gerät installieren oder warten.

VORSICHT!

Dieses Produkt ist ein Klasse 1 Laser, die mit FDA 21 CFR 1040.10 und 1040.11 und IEC 60825-1 entspricht.

VORSICHT!

- Elektrostatische Entladung können elektronische Module beschädigen. Tragen Sie beim Umgang mit Modulen ein Erdungsarmband, um Schäden an den elektronischen Komponenten zu vermeiden. Transportieren oder lagern Sie Module in antistatischem Verpackungsmaterial. Bei der Arbeit an den Modulen, achten Sie darauf, diese stets auf antistatische, elektrisch geerdete Matten zu legen.
- Dieses Produkt und Host-System sind so konzipiert und für die Installation als Teil entweder eine gemeinsame Bonding Network (CBN) oder isoliert Bonding Network (IBN) vorgesehen.
- Falls das Host-System über einen Schutzleiteranschluss (PE) verfügt, muss der PE-Anschluss des Host-Systems mit dem Schutzleiteranschluss (PE) verbunden werden, um sicherzustellen, dass das freiliegende Metall (d. h. Frontblenden, Optikmodule) am Produkt ordnungsgemäß geerdet ist.

HINWEIS

Dieses Produkt erfüllt die EU RoHS Richtlinie. Bitte besuchen Sie www.adtran.com für ausführlichere Informationen zu RoHS/WEEE.

Documentation for Adtran Network Solutions products is available for viewing and download directly from the Adtran Support Community website.

Go to: <https://adtran.com/support>

Registration is required.

Adtran offers training courses on our products, including customized training and courses taught at our facilities or at customer sites.

For inquiries, go to: <http://adtran.com/training>

The following online documents and resources provide additional information for this product:

Adtran Pluggable Optics Compatibility Matrix (online tool, go to: <http://www.adtran.com/pluggableoptics>)

Warranty: Adtran will replace or repair this product within the warranty period if it does not meet its published specifications or fails while in service. Warranty information can be found online at www.adtran.com/warranty.

Trademarks: Brand names and product names included in this document are trademarks, registered trademarks, or trade names of their respective holders.

Copyright © 2022 Adtran Inc. All Rights Reserved.



ADTRAN CUSTOMER CARE:
From within the U.S. 1.888.423.8726
From outside the U.S. +1 256.963.8716
PRICING AND AVAILABILITY 1.800.827.0807

