



Configuring Calling Party Name Timeout on a PRI Interface in AOS

Prior to release A1.05.00, there was a non-configurable, 2-second delay after the receipt of a SETUP message that did not contain calling-party name info on a PRI and before the corresponding INVITE was sent out a SIP trunk. This was done to allow for the ADTRAN device to wait for any potential calling-party name delivery after the initial SETUP message.

Beginning in A1.05.00, the aforementioned delay is configurable. From the PRI interface configuration prompt:

```
(config-pri 1)#calling-party name-facility-timeout  
<0-5> - Time in seconds to wait for facility name message
```

To eliminate the delay, configure 0 seconds for the timeout. The default is 2 seconds.