

Chassis	Part Number	WAN T1	TDM Voice T1//DSX-1	Analog FXS & FXO Interfaces	Ethernet Interfaces	Max Simultaneous TDM to IP Conversions	Max Simultaneous Calls On a SIP Trunk	Max SIP Trunks	Max T.38 Sessions	Memory	Flash
<b>Total Access 900e 3<sup>rd</sup> Gen</b>											
908e 3 <sup>rd</sup> Gen	4243908F2	1-4*	1-4*	8-FXS + 1-FXO	1-GigE + 2-10/100	60	100	12	30	512 MB	128MB
908e 3 <sup>rd</sup> Gen (30-CH DSP)	4243908F5	1-4*	1-4*	8-FXS + 1-FXO	1-GigE + 2-10/100	30	100	12	30	512 MB	128MB
916e 3 <sup>rd</sup> Gen	4243916F2	1-4*	1-4*	16-FXS + 1-FXO	1-GigE + 2-10/100	60	100	12	30	512 MB	128MB
916e 3 <sup>rd</sup> Gen (30-CH DSP)	4243916F5	1-4*	1-4*	16-FXS + 1-FXO	1-GigE + 2-10/100	30	100	12	30	512 MB	128MB
924e 3 <sup>rd</sup> Gen	4243924F2	1-4*	1-4*	24-FXS + 1-FXO	1-GigE + 2-10/100	60	100	12	30	512 MB	128MB
924e 3 <sup>rd</sup> Gen (30-CH DSP)	4243924F5	1-4*	1-4*	24-FXS + 1-FXO	1-GigE + 2-10/100	30	100	12	30	512 MB	128MB
924e 3 <sup>rd</sup> Gen (16-FXS 9-FXO)	4243924F3	1-4*	1-4*	16-FXS + 9-FXO	1-GigE + 2-10/100	60	100	12	30	512 MB	128MB
<b>Total Access 900e 2<sup>nd</sup> Gen</b>											
908e 2 <sup>nd</sup> Gen	4242908L1	1-4#	1-2#	8-FXS + 1-FXO	2-10/100	60	84	12	4	128 MB	32MB
908e 2 <sup>nd</sup> Gen (30-CH DSP)	4242908L5	1-4##	1-2##	8-FXS + 1-FXO	2-10/100	30	84	12	4	128 MB	32MB
916e 2 <sup>nd</sup> Gen	4242916L1	1-4#	1-2#	16-FXS + 1-FXO	2-10/100	60	84	12	4	128 MB	32MB
916e 2 <sup>nd</sup> Gen (30-CH DSP)	4242916L5	1-4##	1-2##	16-FXS + 1-FXO	2-10/100	30	84	12	4	128 MB	32MB
924e 2 <sup>nd</sup> Gen	4242924L1	1-4#	1-2#	24-FXS + 1-FXO	2-10/100	60	84	12	4	128 MB	32MB
924e 2 <sup>nd</sup> Gen (30-CH DSP)	4242924L5	1-4##	1-2##	24-FXS + 1-FXO	2-10/100	30	84	12	4	128 MB	32MB
924e 2 <sup>nd</sup> Gen (16-FXS 9-FXO)	4242924L2	1-4#	1-2#	16-FXS + 9-FXO	2-10/100	60	84	12	4	128 MB	32MB
<b>Total Access 900 2<sup>nd</sup> Gen</b>											
904 2 <sup>nd</sup> Gen	4212904L1	1	1	4-FXS	1-10/100	30	42	3	4	64 MB	32MB
908 2 <sup>nd</sup> Gen	4212908L1	1	1	8-FXS	1-10/100	30	42	3	4	64 MB	32MB
912 2 <sup>nd</sup> Gen	4212912L1	1	1	12-FXS	1-10/100	30	42	3	4	64 MB	32MB
916 2 <sup>nd</sup> Gen	4212916L1	1	1	16-FXS	1-10/100	30	42	3	4	64 MB	32MB
924 2 <sup>nd</sup> Gen	4212924L1	1	1	24-FXS	1-10/100	30	42	3	4	64 MB	32MB