# TRACER 4208 5.8 GHz Integrated Eight T1 Microwave Radio

### **Front View**



## **Rear View**



#### **Physical Interfaces**

- Integrated Ports
- DB-25 Interface
- Eight T1 (DSX-1 Interface Type)

#### **Physical Specifications**

- Chassis: 1U Rack Mount
- Dimensions: 1.72" H, 17.12" W, 10.80" D
- Weight: 7 lbs.
- Operating Temperature: -13°F to 149°F (-25°C to 65°C)
- Mean Time Between Failure (MTBF): 117,939 Hrs

#### **Power Specifications**

- 21-60 VDC (Either Polarity Referenced to Ground)
- Optional 100-250 VAC Auto-Ranging Power Supply
- DC Power Consumption
  - 21 W max
  - **73 BTU max**
- AC Power Consumption
  - **57** W max
  - 197 BTU max
- Max Current Draw: 1.5 A

#### **Administration and Management**

Console (DB-25 Port)

#### **Performance and Design Considerations**

- T1 Bandwidth: 8 T1s max
- Path Distance: Up to 30 Miles Clear Line of Sight
- RF/IF Interface
  - Antenna Connector: female type-N
  - Impedance: 50 ohms
- Transmitter Output Power: +20 dBm max
- Receiver Level Threshold (10<sup>-6</sup> BER)
  - -85 dBm @ 8xT1
  - ∎ -89 dBm @ 4xT1
  - -92 dBm @ 2xT1
- Frequency Band: 5.725 to 5.850 GHz
- Multiple Software Selectable Channel Plans

#### **Agency Approvals**

■ FCC Part 15.247

#### Warranty

- 5 Year (Repair & Return)
- www.ADTRAN.com/Warranty

#### **Product Includes**

- All Tracer units ship with the following:
  - 19" Rackmount Brackets
  - TRACER Documentation CD

## **P/N Information**

| 4208 Chassis & Accessories      | Part Number |
|---------------------------------|-------------|
| TRACER 4208 5.8 GHz (Channel A) | 12804208L1A |
| TRACER 4208 5.8 GHz (Channel B) | 12804208L1B |
| A/C Power Supply                | 1280650L1   |

#### DISCLAIMER

ADTRAN provides the foregoing application description solely for the reader's consideration and study, and without any representation or suggestion that the foregoing application is or may be free from claims of third parties for infringement of intellectual property rights, including but not limited to, direct and contributory infringement as well as for active inducement to infringe. In addition, the reader's attention is drawn to the following disclaimer with regard to the reader's use of the foregoing material in products and/or systems. That is:

ADTRAN SPECIFICALLY DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO, MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. IN NO EVENT SHALL ADTRAN BE LIABLE FOR ANY LOSS OR DAMAGE, AND FOR PERSONAL INJURY, INCLUDING BUT NOT LIMITED TO, COMPENSATORY, SPECIAL, INCIDENTAL, CONSEQUENTIAL, OR OTHER DAMAGES